

Loop Indicator



STI-LI1 is programmable Loop Indicator with graphic display, purposed for transmitters signal visualization.

Configuration:

- from computer
- manual

Adjustments:

- indication numerical and/or barrgraph
- formulas package for signal and reading scaling
- temperature
- level
- flow and integration
- pressure
- others

Technical Data:

- input
4 – 20 mA – two wire scheme
- display
122 x 32 dot. matrix
- power supply
from input signal
- work temperature
from -10 to +70°C
- enclosure
Rittal 125x80x57 IP 66
[EEx] ia IIC